

Cone Speakers / Audio Transformers

CONE SPEAKERS



Q88C10

- Q58H10** 5" cone, 10 oz, 8 ohms, 15 watts.
- Q845D5** Dual 8" cone, 5 oz, 45 ohms, 10 watts.
- Q88D5** Dual 8" cone, 5 oz, 8 ohms, 10 watts.
- Q88D10** Dual 8" cone, 10 oz, 8 ohms, 15 watts.
- Q88C10** Coaxial 8" pievo, 10 oz, 8 ohms, 15 watts.

CONE SPEAKERS WITH TRANSFORMER



8T570

- 8T427** Dual 8" cone, 5 oz, 4 watt 25/70 volt xfmr.
- 8T570** Dual 8" cone, 5 oz, 5 watt 70 volt xfmr.
- 8DT427** Dual 8" cone, 10 oz, 4 watt 25/70 volt xfmr.
- 8DT570** Dual 8" cone, 10 oz, 5 watt 70 volt xfmr.
- 8DT127** Dual 8" cone, 10 oz, 12 watt 25/70 volt xfmr.
- 8CT127** Coaxial 8" pievo, 10 oz, 12 watt 25/70 volt xfmr.

AUDIO TRANSFORMERS



T570

- T427** 4W 25/70 volt with taps at 4, 2, 1, 0.5 watts.
- T570** 5W 70 volt with taps at 5, 2.5, 1, 0.5, 0.25 watts.
- T127** 12W 25/70 volt with taps at 12, 6, 3, 1 watts.
- T1627** 16W 25/70 volt with taps at 16, 8, 4, 2 watts.
- T3227** 32W 25/70 volt with taps at 32, 16, 8, 4 watts.
- T7527** 75W 25/70 volt with taps at 75, 38, 19, 9 watts.

COMMERCIAL SOUND ATTENUATORS



Attenuator

- AXAL48SK** 40 Watts, monaural 8 Ohm L-Pad.
- AXAT35W** 35 Watts, 25/70V.
- AXAT35SK** 35 Watts, 25/70V.
- AXAT35RSK** 35 Watts, with page priority relay, 25/70V.
- AXAT75SK** 75 Watts, 25/70V.

Note: SK = Stainless W = White

DIRECT RADIATING PIEZO TWEETER



Q375TPZ

- Q375TPZ** 3 3/4" Tweeter, 50 watts

Cone Speakers	Q58H10	Q845D5	Q88D5	Q88D10	Q88C10	Q375TPZ
Power Rating (Watts)	15	10	15	15	15	50
Magnet Weight	10 oz	5 oz	5 oz	10 oz	10 oz	—
Freq Resp ± 3db	100Hz-15KHz	90Hz-15KHz	90Hz-15KHz	80Hz-15KHz	80Hz-18KHz	3K - 40K
Sensitivity SPL/1W/1M	93 db	96 db	96 db	100 db	97 db	90 db
Impedance	8 ohms	45 ohms	8 ohms	8 ohms	8 ohms	1K ohm
Depth (w/o transformer)	2 5/32"	2 23/32"	2 23/32"	2 13/16"	2 13/16"	3/4"
Transformer Mounts	2", 2 3/8"	1 3/4", 2", 2 3/8"	1 3/4", 2", 2 3/8"	1 3/4", 2", 2 3/8"	1 3/4", 2", 2 3/8"	—
Cone Speaker w/ transformer	8T427	8T570	8DT427	8DT570	8DT127	8CT127
Cone Speaker	Q88D5	Q88D5	Q88D10	Q88D10	Q88D10	Q88C10
Transformer	T427	T570	T427	T570	T127	T127
Audio Transformers	T427	T570	T127	T1627	T3227	T7527
Power Rating (Watts)	4	5	12	16	32	75
Primary Volts	25, 70	70	70	70	25, 70	25, 70
Freq Resp ± 3db	80Hz-20KHz	80Hz-20KHz	80Hz-20KHz	80Hz-20KHz	80Hz-20KHz	40Hz-18KHz
Primary Taps, Watts	4, 2, 1, 0.5	5, 2.5, 1, 0.5, 0.25	12, 6, 3, 1.5	16, 8, 4, 2	32, 16, 8, 4, 2	75, 37, 18,
Mounting Centers	2"	2"	2"	2"	2 13/16"	2 x 2 1/2"